

Application: Thermostat wire is used in control, heating, air conditioning, intercom system, burglar alarms and other low voltage systems.

Conductor: Solid bare copper

Insulation: PVC

Jacket: PVC

Notes: Available in various jacket colors

DWC Part #	AWG Size	# of Conductors	Conductor Stranding	Weight Lbs/M
1802TSTATPVCBRN	18	2	Solid	18
1803TSTATPVCBRN	18	3	Solid	25
1804TSTATPVCBRN	18	4	Solid	31
1805TSTATPVCBRN	18	5	Solid	38
1806TSTATPVCBRN	18	6	Solid	45
1807TSTATPVCBRN	18	7	Solid	52
1808TSTATPVCBRN	18	8	Solid	56
1809TSTATPVCBRN	18	9	Solid	62
1810TSTATPVCBRN	18	10	Solid	68
1812TSTATPVCBRN	18	12	Solid	80
2002TSTATPVCBRN	20	2	Solid	13
2003TSTATPVCBRN	20	3	Solid	19
2004TSTATPVCBRN	20	4	Solid	23
2005TSTATPVCBRN	20	5	Solid	26
2006TSTATPVCBRN	20	6	Solid	30
2007TSTATPVCBRN	20	7	Solid	34
2008TSTATPVCBRN	20	8	Solid	38
2009TSTATPVCBRN	20	9	Solid	42
2010TSTATPVCBRN	20	10	Solid	46
2012TSTATPVCBRN	20	12	Solid	54

Product details and specifications are subject to manufacturing variations and accepted industry tolerances. Please contact your DWC Account Manager with questions, or to confirm any specific product requirements.

