

CG000222 Rev B

USER GUIDE

Chromium Controller Readiness Test

with Chromium Next GEM Test Chip

FOR USE WITH

Chromium Controller & Next GEM Accessory Kit, PN-120223
(Includes Chromium Next GEM Test Chip, PN-2000199)

Notices

Document Number

CG000222 • Rev B

Legal Notices

© 2019 10X Genomics, Inc (10x Genomics). All rights reserved. Duplication and/or reproduction of all or any portion of this document without the express written consent of 10x Genomics, is strictly forbidden. Nothing contained herein shall constitute any warranty, express or implied, as to the performance of any products described herein. Any and all warranties applicable to any products are set forth in the applicable terms and conditions of sale accompanying the purchase of such product. 10x Genomics provides no warranty and hereby disclaims any and all warranties as to the use of any third-party products or protocols described herein. The use of products described herein is subject to certain restrictions as set forth in the applicable terms and conditions of sale accompanying the purchase of such product. A non-exhaustive list of 10x Genomics' marks, many of which are registered in the United States and other countries can be viewed at: www.10xgenomics.com/trademarks. 10x Genomics may refer to the products or services offered by other companies by their brand name or company name solely for clarity, and does not claim any rights in those third party marks or names. 10x Genomics products may be covered by one or more of the patents as indicated at: www.10xgenomics.com/patents. The use of products described herein is subject to 10x Genomics Terms and Conditions of Sale, available at www.10xgenomics.com/legal-notices, or such other terms that have been agreed to in writing between 10x Genomics and user. All products and services described herein are intended FOR RESEARCH USE ONLY and NOT FOR USE IN DIAGNOSTIC PROCEDURES.

Instrument & Licensed Software Updates Warranties

Updates to existing Instruments and Licensed Software may be required to enable customers to use new or existing products. In the event of an Instrument failure resulting from an update, such failed Instrument will be replaced or repaired in accordance with the 10x Limited Warranty, Assurance Plan or service agreement, only if such Instrument is covered by any of the foregoing at the time of such failure. Instruments not covered under a current 10x Limited Warranty, Assurance Plan or service agreement will not be replaced or repaired.

Support

Email: support@10xgenomics.com

10x Genomics

7068 Koll Center Parkway

Suite 401

Pleasanton, CA 94566 USA

Document Revision Summary

Document Number	CG000222
Title	Chromium Controller Readiness Test User Guide with Chromium Next GEM Test Chip
Revision	Rev A to Rev B
Revision Date	May 2019

General Changes:

- Updates for general minor consistency of language and terms throughout.

Specific Changes:

- Updated note: Firmware Version 4.0 or higher is required in the Chromium Controller used for the Chromium Controller Readiness Test with Chromium Next GEM Text Chip. Also compatible with Chromium Test Chip V1.

Chromium Next GEM Accessory Kit, PN-1000142 (store at ambient temperature)

Product	#	PN (Item)
Chromium Next GEM Test Chip	1	2000199
Chromium Next GEM Secondary Holder	2	3000332
Vortex Adaptor	3	330002
Chip Gaskets, 2 Pack	1	3000072
Magnetic Separator	1	230003
Strip Vortexer	2	230002
Cable USB A MALE - B MALE 1M BLK	1	3000173
Power Cord	1	340001

1.0 Turn on the Chromium Controller

- a. Ensure the Chromium Controller is positioned in accordance with recommendations in the Chromium Controller Specifications.
- b. Turn on the Chromium Controller using the power switch on the back of the unit.
- c. The Chromium Controller touchscreen will indicate initialization is in progress.
- d. When initialization is complete, contact the touchscreen to activate and display the eject button. Press the eject button to eject the tray and remove the foam strip used for protection during shipping.
- e. Press the button again to retract the tray (or the tray will automatically close after 60 sec).



Firmware Version 4.0 or higher is required in the Chromium Controller used for the Chromium Controller Readiness Test with Chromium Next GEM Text Chip. Also compatible with Chromium Test Chip V1.

2.1 Assemble Chromium Next GEM Test Chip



Assemble Chromium Next GEM Test Chip


- Align notch on the chip (upper left corner) and the holder.
- Insert the left-hand side of the chip under the guide. Depress the right-hand side of the chip until the spring-loaded clip engages.
- Close the lid.



2.2 Attach the Gasket

Attach 10x Gasket:

- Attach the gasket by holding the tongue (curved end, to the right) and hook it on the left-hand tabs of the holder (align the notch with the top left-hand corner).
- Gently pull the gasket toward the right and hook it on the two right-hand tabs. Ensure the gasket holes are aligned with the wells.
- DO NOT touch the smooth side of the gasket. DO NOT press down on the top of the gasket after attachment.



3.0 Run the Chromium Controller

- a. Contact the touchscreen of the Chromium Controller to display options.
- b. Press the eject button on the touchscreen to eject the tray.
- c. Place the assembled chip with the gasket in the tray (align the diagonal etchings on the top left corner of the Chromium Next GEM Secondary Holder and the back left corner of the tray). Press the button to retract the tray.
- d. Confirm the Chromium Test program on screen. Press the play button.
- e. At the completion of the run (~3 min), the Chromium Controller will chime. Press the button to eject the empty tray.
- f. If there are any problems during this process, contact support@10xgenomics.com for further assistance.
- g. Save the Chromium Next GEM Secondary Holder for use with your Chromium Controller. The 10x Gasket and Test Chip should also be stored.



Firmware Version 4.0 or higher is required in the Chromium Controller used for the Chromium Controller Readiness Test with Chromium Next GEM Text Chip.

Also compatible with Chromium Test Chip V1.

