

Low-Voltage Transformers

	SMART	PROFESSIONAL							CONTRACTOR				PLUS					MANUAL			STANDARD	
	15SCT300SS	15PR75SS	15PR100SS	15PR200SS	15PR300SS	15PR600SS	15PR900SS	15PR1200SS	15CS75SS	15CS150SS	15CS300SS	15CS600SS	15PL75AZT	15PL100AZT	15PL200AZT	15PL300AZT	15PL600AZT	15M100AZT	15M200AZT	15M300AZT	15E60BK	15E120BK
Wattage (VA)	300	75	100	200	300	600	900	1200	75	150	300	600	75	100	200	300	600	100	200	300	60	120
App controlled, Wi-Fi® enabled	Yes	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	No	
Photo Cell Receptacle	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No	Built in	
Timer Compatible	In app	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Built in Timer	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No	Built in Timer	
Taps & Terminal Block Configurations	(3) 15V easy connect taps	15V easy connect tap	(2) 15V easy connect angled taps			12, 13, 14, 15V easy connect taps			12, 15V screw type taps	12, 13, 14, 15V easy connect taps			15V easy connect tap	12, 13, 14, 15V easy connect taps			12V screw type tap	12V easy connect tap	12, 13, 15V easy connect taps	12.5V screw type taps		
Commons	3	1	1	2	2	2	3	4	1	1	1	2	1	1	1	1	2	1	1	1	1	1
Zoning	3	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Thermal Cut Off Primary	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Secondary Breaker	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Mag	Therm	Therm	Mag	Therm	Therm
Core and Coil Type	Toroid	Toroid	E.I.	E.I.	E.I.	E.I. & Toroid	Toroid	Toroid	Toroid	Toroid	Toroid	Toroid	Toroid	E.I.	E.I.	E.I.	E.I.	E.I.	E.I.	E.I.	E.I.	E.I.
Power Cord	6' 3-wire # 18-3SJTW	6' 3-wire # 18-3SJTW				6' 3-wire # 16-3SJTW	6' 3-wire # 14-GA SJTW	6' 3-wire # 18-3SJTW				6' 3-wire # 18-3SJTW			6' 3-wire # 16-3SJTW	6' 3-wire # 18-3SJTW			6' 2-wire # 18-2SJTW			
Housing Finish	#304 Stainless Steel	#304 Stainless Steel							#304 Stainless Steel				Textured Architectural Bronze Powder Coat					Textured Architectural Bronze Powder Coat			Composite	

Mounting hardware included with all models. 600W, 900W and 1200W Transformer models are manufactured in intervals of 300W (VA) circuits. National Electric Code and Underwriters Laboratories require that wiring, where concealed or extended through a building wall, must be enclosed in conduit. All transformers are for use with outdoor low-voltage lighting.