

Fuse table

TIME Direct / Indirect 1140, 1420

Maximum loading of automatic of circuit breakers

Driver: Xitanium 36W 0.3-1A 54V TD 230V	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25
Number of drivers stated to the right	37	49	61	75	94	23	29	36	45	56

Note! There are 2 drivers / DALI address in each luminaire.
(Ex. 18 luminaires on a B16 fuse)

* Input voltage 230V, Time measured at 50% Ipeak

TIME Direct / Indirect 1700, 2260, 2820

Maximum loading of automatic of circuit breakers

Driver: Xitanium 36W 0.3-1A 54V TD 230V	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25
Number of drivers stated to the right	25	32	41	50	62	15	19	24	30	37

Note! There are 2 drivers / DALI address in each luminaire.
(Ex. 12 luminaires on a B16 fuse)

* Input voltage 230V, Time measured at 50% Ipeak