

Crescent

DA-HDTV-SDI

HDMI to SDI converter with SDI Loop Out



DA-HDTV-SDI

Key Features

- Compact HDMI 1.4 to SDI converter
- HDMI loop out
- HDMI extender input (RJ45)
- Passes 4 channels of HDMI audio
- Built-in interlacer (1080P to 1080i)
- Built-in multi-format test patterns
- 2 SDI outputs
- Unbalanced analog stereo output
- 5V DC
- Also available in openGear card

Front View



HDMI Loop out
HDMI input
RJ45 (HDMI) input
Scan button to switch RJ45/HDMI

Rear View



5V DC input
Rotary switch for 1080i output or patterns
Analog audio breakout
2 x SDI outputs

Related Products

DA-HDTV-SDI-UHD
HDMI 2.0 to 12G converter

DA-SDI-HDTV-II
SDI to HDMI converter

DA-SDI-HDTV-UHD
12G to HDMI 2.0 converter

Specifications

Model	DA-HDTV-SDI
Description	HDMI to SDI converter with looping input and 2 x SDI outputs
Inputs	1 x HDMI, 1x RJ45, supports up to HDMI 1.4 up to 1080P
Outputs	2 x SDI (1080P, 1080i, 720P, 480i)
Audio	Passes 4 channels of HDMI audio and stereo audio via 3.5 mm phone jack
Power	5V 3A
Weight	1.2 lb (0.55 kg)
Dimension	62 x 113 x 40 mm (W x D x H)