



BACK-UP ALARMS



SAE
TYPE
C
EA515C
EA520C
only

SAE
TYPE
D
EA505C
EA515C
only

SAE
TYPE
F
SA930C
SA950C
only

CE

**UK
CA**

R10

AMECA

COMBO ALARM™ SERIES

Two Selectable Sounds

ECCO's Combo Alarm™ Series combines two back-up alarm sounds into one device, letting operators select between sounds via two separate power wires. Connect one power wire to emit one sound only, or connect both power wires for the ability to switch between both sounds via the double engage reverse feature. Two selectable sounds allow fleets, work trucks, and municipalities to adhere to local guidelines using one alarm instead of two. Most models pair tonal (beep beep) and Multi-Frequency™ (white noise shhh shhh) sound into one device, and a tonal-only model is also available. Smart Alarm® models listen to ambient noise and adjust output volume in real time. Every model runs 12-24 VDC, is built in durable glass-filled nylon housing and backed by our 2-year no-hassle warranty.

Models

PART NO.	TYPE	VOLTS	DECIBELS (SOUND 1)	DECIBELS (SOUND 2)	AMPS
EA505C	-	12-24	87, MFA	87, Tonal	1.0
EA515C	-	12-24	87, MFA	97, Tonal	1.0
EA520C	-	12-24	97, MFA	97, Tonal	1.0
SA930C	Smart	12-24	77-102, Tonal	102, Constant	1.0
SA950C	Smart	12-24	77-102, Tonal	77-97, MFA	1.0

Design Features

- Combines two back-up alarms into one device with two selectable sounds for double the function
- Choose between tonal (beep beep) and Multi-Frequency™ (white noise shhh shhh)
- Connect one power wire to trigger a single sound only
- Connect both power wires and shift into reverse twice within 1 second, or connect to a rocker switch, to switch between sounds
- Smart Alarm® models have the ability to adjust output up to 5dB above ambient noise

