

FUSE TABLE FOR QUAD PIXEL

Drivers

940/930 Touch and DALI, 1500-3500lm

Driver: Xitanium 36W WH 0.15-1.05A 54V TD/Is

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	33	43	54	67	83	20	26	32	40	50	5,5A 55 µs*

*Input voltage 230V, Time measured at 50% Ipeak

940/930 Touch and DALI, 4150-5000lm

Driver: Xitanium 50W WH 0.7-1.5A 54V TD/Is

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	28	36	46	56	70	17	22	27	34	42	5,5A 55 µs*

*Input voltage 230V, Time measured at 50% Ipeak

940/930 ORT 1500lm

Driver: Xitanium 20W WH 0.15-0.5A 54V SR Is 230V

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	104	135	170	208	260	63	81	100	125	156	6,7A 30 µs*

*Input voltage 230V, Time measured at 50% Ipeak

940/930 ORT 3500lm

Driver: Xitanium 36W WH 0.3-1.05A 54V SR Is 230V

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	33	43	54	67	83	20	26	32	40	50	9A 25 µs*

*Input voltage 230V, Time measured at 50% Ipeak

940/930 ORT 4150-5000lm

Driver: Xitanium 50W WH 0.7-1.5A 54V SR Is 230V

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	28	36	46	56	70	17	22	27	34	42	9,4A 35 µs*

*Input voltage 230V, Time measured at 50% Ipeak

Tunable White

Tunable white, Touch and DALI and ORT, 3500lm

Driver: Helvar LC45iC-DA-100-900

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	35	46	58	71	88	21	28	34	43	53	29A 153 µs*

*Input voltage 230V, Time measured at 50% Ipeak

Tunable white, Touch and DALI and ORT, 4150-5000lm

Driver: Tridonic LCA 85W 600-1800mA DT8 Ip PRE

	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Automatic circuit breaker type											I max Time
Number of drivers	16	20	25	32	39	9	12	15	19	23	32 215 µs*

*Input voltage 230V, Time measured at 50% Ipeak