

MT Hood

Dante -AA

Dante to 4 channel analog (unbalanced) audio decoder



Dante-AA

Key Features

- Decodes Dante audio input to 4 channels of unbalanced analog audio outputs
- Freely choose any 4 channels of Dante audio on the network to be decoded
- Ideal for working with analog audio speakers

Front View



- 4 x BNC for unbalanced audio outputs (comes with BNC to RCA adapters)
- 1 x RJ45 for Dante input
- 1 x Sync Status LED
- 1 x Power Status LED
- 1 x 12V DC Power Inlet

Specifications

Model	Dante-AA
Description	Decodes 4 channel of analog audio from Dante
Inputs	1 x RJ45
Outputs	4 x unbalanced analog audio
Power	12V 1A
Dimension	140 x 114 x 35 mm
Weight	2.85 lb (1.3 kg)