

Low-Voltage Transformers

	In-Ground Series		Standard Series		Pro-Contractor Series					Smart
	15IGT100	15IGT300	15E60BK	15E120BK	15PC75SS	15PC150SS	15PC300SS	15PC600SS	15PC900SS	15SCT300SS
Wattage (also max VA load)	100	300	60	120	75	150	300	600	900	300
Photo Cell	Not Compatible	Not Compatible	Built-in	Built-in	Accessory Plug Included	Accessory Plug Included	Accessory Plug Included	Accessory Plug Included	Accessory Plug Included	Not Compatible
Timer	Not Compatible	Not Compatible	Mechanical, Built-in	Mechanical, Built-in	Mechanical, Built-in	Accessory Socket Included	Accessory Socket Included	Accessory Socket Included	Accessory Socket Included	Control with Kichler Connects
Output Taps*	(2) 15V	(3) 15V	12.5V	12.5V	(2) 15V	(2) 15V	(2) 15V	(4) 15V	(3) 15V	(3) 15V
Commons	1	1	1	1	2	2	2	2	3	3
Terminal Block Style	Wire		Screw		Easy Connect Angled					
Zoning	No									(3) Zones - control with Kichler Connects™ app
Coil Type	Toroid		E.I.		Toroid					
Housing Finish	Plastic				#304 Stainless Steel					
Primary Thermal Cut Off	Yes									
Secondary Breaker	Mechanical Switch		Push Button		Mechanical Switch				Electronic	
Power Cord	None		18AWG/2 Cord, SJTW, 105°C, 72"		16AWG/3 Cord, SJTW, 105°C, 72"				16AWG/3 Cord, SJTW, 105°C, 72"	
Dimensions	9.5"Dia. x 13.25"L		3.6"W x 4"D x 6.63"L		3.75"W x 5"D x 9.5"L	6.25"W x 6.25"D x 13.25"L	6.25"W x 6.25"D x 13.25"L	7.25"W x 7"D x 14.5"L	9"W x 8"D x 15.5"L	7.4"W x 6"D x 13.78"L
Door/Cover	Screw on Plastic Top Plate		Clear Plastic Cover		Right to Left with Latch					
Knockouts	(4) 3/4" SCH40 PVC		None		(2) 3/4" SCH40 PVC		(4) 3/4" SCH40PVC (1) 1.5" SCH40 PVC			
Warranty	10 Years		5 Years		Lifetime**				5 Years Electronics/ Lifetime Enclosure & Toroid	

Mounting hardware included with all models. National Electric Code and Underwriters Laboratories require that wiring, where concealed or extended through a building wall, must be enclosed in conduit. All transformers are for use with outdoor low-voltage lighting. *Kichler 12V Landscape lighting fixtures are designed to operate between 9 and 15 volts without any loss of function or impact to life. **As long as the original consumer purchases or commercial purchaser owns the transformer.