# Polycom® VVX® 300 Series Business Media Phones user guide

The information in this guide applies to the VVX<sup>®</sup> 300 Series phones. Configurations vary and the screen displays used in this guide may not reflect those on your phone. For more information please contact your Shaw Business Support Representative.

# Viewing your phone keys and hardware



Feature	Description	Feature	Description
Speaker	Provides ringer and hands-free (speakerphone) audio output.	Navigation keys/Select key	Scrolls through information or options displayed on the phone's screen. Selects
Dialpad	Enables you to enter numbers, letters, and special characters. You can also use the dialpad keys to select menu items that have index numbers.	Headset key	a field of displayed data. Enables you to place and receive calls through a headset. The key glows green when an analog headset is activated.
Security slot	Enables you to connect the back of your phone to a laptop cable lock so you can secure it to a desktop.	Speakerphone key	Enables you to place and receive calls using the speakerphone. The key glows green when activated.
Message Waiting Indicator	Flashes red to indicate new messages.	Mute key	Mutes your audio during calls and conferences. The key glows red when audio is muted.
Home key	Enables you to press from any screen to display Home view. From Home view, press to display other phone views.	Volume keys	Adjusts the volume of the handset, headset, speaker, and phone's ringer.
		Microphone	Transmits sound from your phone to other phones.
Screen	Shows a 2.2-inch diagonal screen with a backlight.		ourer priories.



# Polycom® VVX® 300 Series Business Media Phones user guide

## Home view

Home view displays icons you can tap to access phone functions.



# **Directories View**

Directories view displays the following four options:



# **Contact Directory**

This contains any user and group personal contact lists. Typically, this would be contacts outside your company.

# **Recent Calls**

This is a list of recent calls. You can select an entry and press the Dial key to call that number.

# **Viewing Recent Calls**

From Lines view, do one of the following:

- Press the right arrow key to view the recent Placed Calls.
- Press the left arrow key to view the recent Received Calls.
- Press the down arrow key to view the recent Missed Calls.

• Press the up arrow key to view Favorites.

From the Recent Calls list, press **Sort** to sort and order calls, press **Type** to display only certain calls, or select a call record to call the person.

# **Broadsoft Enterprise Directory**

This is a searchable list of all the users within your company. You can select an entry and press the Dial key to call that number.



You can enter a name to search using the phone's dial pad. To see the entire directory, enter<sup>\*</sup> into the search box.



From the Advanced search screen, you can search in multiple ways, by first or last name, phone number, or by extension.



**Note:** If you do not wish to have your name and number listed in the Enterprise Directory, contact Shaw Business Technical Support at 1-877-742-9249 to have your privacy setting updated.

## **Calls view**

If your phone has one or more calls, you can access Calls view. Call color indicates status:



- Medium greg—Active can
- Dark grey—Incoming call
- White—Held call

Use the up and down arrow keys to select a call (highlight it). The soft keys control the highlighted call.

# **Entering data**

Use the dialpad keys to enter information. To backspace, press **Backspace**.

To type with the dialpad keys, press a key repeatedly to view the character options and stop to select. To type other characters, press **Encoding** or **Mode**. When using the dialpad keys, use the **1**, **\***, **0**, and **#** keys.

# About calls

Only one call can be active at one time. You can use the handset, speakerphone, or headset for calls. During a call, you can change modes by picking up the handset, or by pressing () or ()

If you navigate away from your call(s), press @to see Active Call or Calls view.



\*VoIP phone emergency 9-1-1 features differ from traditional 9-1-1 services. Visit business.shaw.ca/smartvoice911 for more information.

# Polycom® VVX® 300 Series Business Media Phones user guide

#### Tip: Switching between Lines and Calls view

When in Calls view, switch to Lines view by pressing More > Lines. Switch back to Calls view by pressing More > Calls.

## Placing calls\*

#### Tip:

#### Placing conference calls

If you have an active and held call, press Join to set up a conference.

Pick up the handset, or press () or () Enter the phone number, and press Send.

Or enter the phone number first, then press **Dial**, pick up the handset, or press **(i)** or **(D)**.

From Lines view: Press the phone Line key, enter the phone number, and press **Send**. From Home view: Select **New Call** using the left and right arrow keys. Enter the phone number, and press **Send**.

# Tip: Placing calls quickly

Select a recent call or Favorite, or select a contact's phone number in the Contact Directory.

## **Answering calls**

To answer with the speakerphone, press or tap **Answer**. To answer with the handset, pick up the handset. To answer with a headset, press **O**. To answer a new call while on an active call, press **Answer**. The current call will be held

## **Ending calls**

To end an active call, replace the handset, press (), or press (). Or, press **End Call**. To end a held call, navigate to Calls view and highlight the held call. Press **Resume**, and press **End Call**.

## **Holding calls**

From Calls view, press **Hold** or **(**). Remember to highlight the call first. To resume a held call, press **Resume** or **(**) again.

## **Transferring calls**

From Calls view, press **Transfer** or  $( \mathfrak{S} )$ , and call the other party. When you hear the ringback tone, or after you talk with the other party, press **Transfer** or  $( \mathfrak{S} )$ again. Press **Blind** to complete a transfer without waiting for the ringback tone.

## **Forwarding calls**

To enable call forwarding, press **Forward** from Home or Lines view. Select the forwarding type to enable, enter a forwarding number, and press **Enable**.

To disable call forwarding, press **Forward** from Home or Lines view, select the forwarding type to disable, and press **Disable**.

To enable per-call forwarding: As your phone rings, press **Forward**, enter the forwarding number, and press **Forward**.

# **Placing Conference Calls**

Call the first party, and after the call connects, press **More**, and select **Confrnc**. Then, dial and connect with the second party and press **Confrnc** again. From Lines or Calls view, you can:

- Press Hold to hold all participants.
- Press **End Call** to remove yourself from the call, but keep the other participants connected.
- Press Manage (if available) to manage each participant.
- Press **Split** to end the conference and hold all participants.

## **Favorites**

Favorites are contacts you call most often. Your Favorites list displays all your Favorites. A smaller number of Favorites displays in Lines view.

 To view your Favorites list—From Home view, press and select
Directories> Favorites.  To make a contact a Favorite— Navigate to your Contact Directory and select the contact. Press Info, press More, and select Add to Favorites. Press Yes to confirm.

#### Tip: What does the star mean?

A star, ★ ,indicates a favourite.

## Listening to voicemail

An envelope, And Select Message from Home view or press (and select Message Center.) Press Connect and follow the prompts or dial \*98.

#### Muting the microphone

During a call, press 🐼 so other parties can't hear you. To disable Mute, press again.

This applies to calls using the handset, headset, and speakerphone.

## **Using Do Not Disturb**

To enable or disable ringing, press **DND** from Home or Lines view. When Do Not Disturb is enabled, the DND icon, **I**, displays in the status bar and beside the appropriate Line key.

#### **Adjusting volume**

To change call volume, press during a call. To change the ringer volume, press when the phone is idle or ringing.

